

E3250 115V 50HZ HUK

ENERGY AT FAIR PRICE



Simple professional generator. Pramac has designed this generator to ensure a high performance level at attractive price. Powerful and strong generator; easy to maintain, it will be soon essential to all your activities.

Main Features		
Frequency	Hz	50
Voltage	V	115
Power factor	cos φ	0.9
Phase		1

Power Rating		
Emergency Standby Power ESP	kVA	2.9
Emergency Standby Power ESP	kW	2.6
Continuous power COP	kVA	2.5
Continuous power COP	kW	2.2

Ratings definition (ISO-8528)

ESP - Emergency Standby Power: It is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 h of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 h of operation shall not exceed 70 % of the ESP.

COP - Continuos Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedure being carried out as prescribed by the manufacturers.

Engine specifications		
Engine Brand		Honda
Model		GX160
Engine cooling system		Air
Displacement	CM3	163
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Petrol
Oil capacity	I	0.6
Starting system		Recoil




Alternator Specifications		
Туре		
Class		Н
IP protection		23
Poles		2
Frequency	Hz	50
Voltage regulation system		Capacitor

Dimensional data		
Length	(L) mm	625
Width	(W) mm	455
Height	(H) mm	455
Dry weight	kg	38
Fuel tank capacity		3.1

Autonomy		
Fuel consumption at 75% of Load	l/h	0.88
Fuel consumption at 100% of Load	l/h	1.17
Running time at 75% of load	h	3.52
Running time at 100% of load	h	2.65

Noise level		
Guaranteed noise level (LWA)	dB(A)	94
Noise pressure level @ 7 m	dB(A)	66

SOCKET TYPE



 \otimes 2023 | PR Industrial S.r.L unipersonale – Loc. II Piano – 53031 Casole d'Elsa (SI) – ITALY. Company subject to the management and coordination of Generac Power Systems Inc.| All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice

-